


54/7474
54H/74H74
54S/74S74
54LS/74LS74

**DUAL D-TYPE POSITIVE EDGE-
 TRIGGERED FLIP-FLOP**

**CONNECTION DIAGRAMS
 PINOUT A**



DESCRIPTION — The '74 devices are dual D-type flip-flops with Direct Clear and Set inputs and complementary (Q, \bar{Q}) outputs. Information at the input is transferred to the outputs on the positive edge of the clock pulse. Clock triggering occurs at a voltage level of the clock pulse and is not directly related to the transition time of the positive going pulse. After the Clock Pulse input threshold voltage has been passed, the Data input is locked out and information present will not be transferred to the outputs until the next rising edge of the Clock Pulse input.

TRUTH TABLE
 (Each Half)


INPUT	OUTPUTS	
@ t_n	@ $t_n + 1$	
D	Q	\bar{Q}
L	L	H
H	H	L

Asynchronous Inputs:


LOW input to \bar{S}_D sets Q to HIGH level
 LOW input to \bar{C}_D sets Q to LOW level
 Clear and Set are independent of clock
 Simultaneous LOW on \bar{C}_D and \bar{S}_D
 makes both Q and \bar{Q} HIGH

H = HIGH Voltage Level
 L = LOW Voltage Level
 t_n = Bit time before clock pulse.
 $t_n + 1$ = Bit time after clock pulse.

PINOUT B



LOGIC SYMBOL



Vcc = Pin 14 (4)
 GND = Pin 7 (11)

ORDERING CODE: See Section 9

PKGS	PIN OUT	COMMERCIAL GRADE	MILITARY GRADE	PKG TYPE
		Vcc = +5.0 V \pm 5%, TA = 0°C to +70°C	Vcc = +5.0 V \pm 10%, TA = -55°C to +125°C	
Plastic DIP (P)	A	7474PC, 74H74PC 74S74PC, 74LS74PC		9A
Ceramic DIP (D)	A	7474DC, 74H74DC 74S74DC, 74LS74DC	5474DM, 54H74DM 54S74DM, 54LS74DM	6A
Flatpak (F)	A	74S74FC, 74LS74FC	54S74FM, 54LS74FM	3I
	B	7474FC, 74H74FC	5474FM, 54H74FM	